


# WORKING TIME ON ONE CHARGE



BATTERY	536Li XP®			T536Li XP®		536LiPX	536LiPT5/ 536LiP4		536LiRX/536LiLX		536LiHE3/536LiHD70X/536LiHD60X		536LiBX*/536LiB	
	CARPENTER	PRUNING	LOG CUT	PRUNING	CLEARING	PRUNING	LIGHT	TOUGH	LIGHT	TOUGH	LIGHT	TOUGH	LIGHT	TOUGH
<b>BLi10</b>	1 h 10 min	30 min	15 min	50 min	30 min	40 min	30 min	15 min	50 min	25 min	15 min	10 min		
<b>BLi20</b>	2 h 25 min	1 h	25 min	1 h 40 min	1 h 5 min	1 h 30 min	1 h 5 min	30 min	1 h 35 min	50 min	30 min	15 min		
<b>BLi100</b>	1 h 35 min	40 min	15 min	1 h 5 min	40 min	50 min	40 min	20 min	1 h 5 min	30 min	20 min	10 min		
<b>BLi200</b>	3 h 5 min	1 h 15 min	35 min	2 h 10 min	1 h 25 min	1 h 55 min	1 h 25 min	40 min	2 h 5 min	1 h	35 min	20 min		
<b>BLi300</b>	5 h 35 min	2 h 15 min	1 h	3 h 55 min	2 h 30 min	3 h 30 min	2 h 30 min	1 h 15 min	3 h 45 min	1 h 50 min	1 h 5 min	40 min		
<b>BLi520X</b>	8 h 40 min	3 h 30 min	1 h 30 min	6 h	3 h 50 min	5 h 20 min	3 h 50 min	1 h 50 min	5 h 50 min	2 h 50 min	1 h 40 min	1 h		
<b>BLi940X</b>	15 h 40 min	6 h 20 min	2 h 50 min	11 h	7 h	9 h 40 min	7 h	3 h 30 min	10 h 30 min	5 h 10 min	3 h 10 min	1 h 50 min		



BATTERY	436Li			436LiB		336LiC		115iL	115iHD45	120i	LC 141VLi	LC 141Li
	CARPENTER	PRUNING	LOG CUT	LIGHT	TOUGH	LIGHT	TOUGH			PRUNING		
<b>BLi10</b>	1 h 20 min	30 min	15 min	15 min	10 min	25 min	15 min	30 min	50 min	—	—	20 min
<b>BLi20</b>	2 h 40 min	1 h 5 min	30 min	35 min	20 min	50 min	30 min	1 h	1 h 35 min	35 min	25 min	30 min
<b>BLi100</b>	1 h 45 min	40 min	20 min	25 min	15 min	30 min	20 min	40 min	1 h 5 min	—	20 min	25 min
<b>BLi200</b>	3 h 25 min	1 h 25 min	40 min	45 min	25 min	1 h	35 min	1 h 15 min	2 h 5 min	45 min	30 min	35 min
<b>BLi300</b>	6 h 10 min	2 h 30 min	1 h 10 min	1 h 20 min	50 min	1 h 50 min	1 h 5 min	—	—	—	1 h	1 h 5 min
<b>BLi520X</b>	9 h 30 min	3 h 50 min	1 h 50 min	2 h	1 h 10 min	2 h 50 min	1 h 40 min	3 h	4 h	1 h 30 min	—	—
<b>BLi940X</b>	17 h 10 min	7 h	3 h 20 min	3 h 50 min	2 h 20 min	5 h 10 min	3 h 10 min	5 h 30 min	7 h 30 min	3 h	—	—

The runtimes are up-to times and correspond to work time using savE™: actual work, basic maintenance and movement /climbing needed for generic operations.  
500 series – Full time user 300/400 series – Part-time user 100 series – Occasional user \*Requires BLi backpack batteries.

## CHARGE TIME



BATTERY / CHARGER	QC500		QC330		QC80		QC80F	
	CHARGING LEVEL		CHARGING LEVEL		CHARGING LEVEL		CHARGING LEVEL	
<b>BLi10</b>	25 min	40 min	25 min	40 min	50 min	1 h 10 min	50 min	1 h 10 min
<b>BLi20</b>	25 min	40 min	25 min	40 min	1 h 50 min	2 h 10 min	1 h 50 min	2 h 10 min
<b>BLi100</b>	30 min	50 min	30 min	50 min	1 h 5 min	1 h 25 min	1 h 5 min	1 h 25 min
<b>BLi200</b>	30 min	50 min	30 min	50 min	2 h 25 min	2 h 40 min	2 h 25 min	2 h 40 min
<b>BLi300</b>	35 min	1 h	55 min	1 h 20 min	4 h	4 h 20 min	4 h	4 h 20 min
<b>BLi520X</b>	55 min	1 h 20 min	1 h 30 min	1 h 55 min	6 h 30 min	8 h 30 min	6 h 30 min	8 h 30 min
<b>BLi940X</b>	1 h 25 min	2 h 25 min	2 h 30 min	3 h 25 min	10 h 40 min	11 h 50 min	10 h 40 min	11 h 50 min